



Fig 2-12 Interwiring of ADF Receiver AD 3502-(), Antenna AN 3500 and Converter and Indicator ID 3502-()

Bemerkungen / NOTES :

- Dargestellte Ausführung: Antennenmontage unten.
 INTERWIRING AS SHOWN IS FOR A BOTTOM MOUNTED ANTENNA
- ② Antennenmontage oben: Kabelanschluß von P1/1 an P1/9 legen.
 Abschirmkabelanschlüsse P1/5 und P1/6 vertauschen.
 FOR TOP MOUNTED ANTENNA CHANGE SOLDERING CONNECTIONS FROM P1/1 TO P1/9.
 INTERCHANGE SHIELD CABLE CONNECTIONS FROM P1/5 TO P1/6.
- ③ RG58A/U, oder anderes gleichwertiges 50 Ohm Koaxkabel verwenden.
 USE RG58A/U, OR OTHER EQUIVALENT 50 OHM COAXIAL CABLE
- ④ Alle nicht bezeichneten Kabel AWG22.
 UNLESS OTHERWISE NOTED: ALL WIRES ARE TO BE AWG22.